



   SCAN MY QR! to register e-Warranty soundtech.sg Instruction Manual For ROMI ADAPTOR WITH GaN PD 45W USB QUICK CHARGER Model: TA-845C	Introduction Thank you for choosing SOUNDTECH product, we truly appreciate your support and trust in our brand. Before embarking your first experience in using this product, please kindly read and understand this manual thoroughly in order to fully understand the product, its functions and usage correctly. Important Note • Use this travel adaptor only as described in this manual. Not doing so may cause fire, electric shock or injury to persons. • This product is intended for indoor use and in dry location only. • This product does not convert voltage (AC + AC). In order to avoid possible damage to your device or other safety hazards, please make sure the power outlet you intend to use has the proper voltage to run your device before using this adaptor. • Each country has its own regulations (voltage, plug type, etc.) regarding the use of travel adaptors, please do a check in each country before use. • No grounding, this product is to be for use with unearthed or double insulated appliances only. • Do not continue using the product if the exterior housing is damaged or functionality of unit is defective. • Do not operate the travel adaptor in the presence of explosive and/or flammable fumes, expose it to liquid or moist / humid environment. • Do not handle the product with wet hands. • Do not use with connecting AC powered devices that requires power over 250V~2500W or 100V~1000W. • Keep the product out of reach of children. • The travel adaptor unit comes with three(3) years warranty. Terms and conditions apply. Damages caused by wrong treatment or operation, by false placement or storage, improper connection or installation, as well as force or other external influences are not covered by this warranty. • Please register the warranty online once you purchased this travel adaptor unit. • When the product is still under warranty and you need to send it to our service care centre for repair, please bring along your product's purchase receipt/invoice and e-warranty registration confirmation email for verification purpose.	• Never attempt to disassemble/repair/modify the product and move any inside components or parts, else it will void your warranty. In event of product damage / breakage, stop use immediately and replace / repair. • Do not rub away or destroy words of rating label or warning instructions from the product. Features • The travel adaptor is applicable for usage in more than 180 countries with its built-in US / AUS / EU / UK plugs. • Product housing is made of flame-retardant PC material. • Universal socket-outlet, allows multiple plug types plug-in. • Built-in safety shutters protect user from the direct touch of the live parts on the product's socket-outlet. • Only one plug-type can be operated at a time, other plug-pins are locked automatically. • Plug-pin can only be released and retracted to its original position by first pressing down the "Retract" button. • Built-in Auto-Resetting Fuse: when short-circuit or overloading situation happens, the travel adaptor will automatically power off to limit and protect the circuit. After a few minutes, once the auto-resetting fuse cools down, it will continue its operation normally. No physical fuse replacement needed. • USB ports: Power Delivery (PD) 3.0 and Qualcomm Quick Charge (QC) 3.0 power-charging technologies. • USB Protections: Over-temperature, over-current, over-voltage, over-charging, short circuit, overload, low-voltage, chip protection. • Compatible in charging iPad, iPhone, Android smartphones, tablets, digital cameras, portable game consoles, MP3 players, Bluetooth headsets/speakers, power banks, etc. 	Product Details  Specifications Model: TA-845C Input: 100~250V AC, 50/60Hz Auto-Resetting Fuse Rating: 10A Rated Power: 1000W at 100V AC, 2500W at 250V AC Total USB Output: 45W Max. USB-C1 + C2 / C3 / USB-A Single Output: 5V/3A, 9V/3A, 12V/3A, 20V/2.25A (45W Max) PPS: 3.3~16V/3A, 3.3~21V/2.25A USB-C1 + USB-C2 / USB-C3 + USB-A: 5V/3A (15W Max) USB-C1 + USB-C3: 5V/3A, 9V/2A, 12V/1.67A (20W Max) + 5V/3A, 9V/2A, 12V/1.67A (20W Max) USB-C2 + USB-C3: 5V/3A, 9V/2A, 12V/1.67A (20W Max) + 5V/3A, 9V/2A, 12V/1.67A (20W Max) USB-C1 + USB-A: 5V/3A, 9V/2A, 12V/1.67A (20W Max) + 5V/3A, 9V/2A, 12V/1.5A (18W Max)	USB-C2 + USB-A: 5V/3A, 9V/2A, 12V/1.67A (20W Max) + 5V/3A, 9V/3A, 12V/2.25A (27W Max) USB-C1 + [USB-C2 + USB-A]: 5V/3A, 9V/2A, 12V/1.67A (20W Max) + 5V/3A (15W Max) USB-C2 + USB-C3 + USB-A: 5V/3A, 9V/2A, 12V/1.67A (20W Max) + 5V/3A (15W Max) + 5V/3A (15W Max) [USB-C1 + USB-C2] + USB-A: 5V/3A (15W Max) + 5V/3A, 9V/3A, 12V/2.25A, 20V/1.35A (27W Max) USB-C1 + USB-C2 + USB-C3 + USB-A: 5V/6A (30W Max) World Travel Adaptor with GaN PD 45W USB Quick Charger (3 PD USB-C Ports & 1 QC USB-A Port). Applicable for usage in more than 180 countries.  US Plug-Pin Operation • Press down and slide out the "US" button to slide out the "US" plug-pin. Ensure the plug-pin is fully-extended and locked in position. To Retract • Firstly, press down and hold the "Retract" button; • Then press down and slide in the "US" button to retract the "US" plug-pin back to its original position. Compatible Countries USA, Canada, Japan, China, Taiwan, Caribbean, North & South America, Philippines, Thailand
---	---	---	--	--

 AUS Plug-Pin Operation • Press down and slide out the "AUS" button to slide out the "AUS" plug-pin. Ensure the plug-pin is fully-extended and locked in position. To Retract • Firstly, press down and hold the "Retract" button; • Then press down and slide in the "AUS" button to retract the "AUS" plug-pin back to its original position. Compatible Countries Australia, Argentina, Fiji, China, New Zealand, Papua New Guinea  EU Plug-Pin Operation • Press down and slide out the "EU" button to slide out the "EU" plug-pin. Ensure the plug-pin is fully-extended and locked in position. To Retract • Firstly, press down and hold the "Retract" button; • Then press down and slide in the "EU" button to retract the "EU" plug-pin back to its original position. Compatible Countries Africa, Europe, France, Germany, Greece, Russia, Korea, Switzerland, U.A.E, Thailand, Indonesia, Denmark, Finland, Norway, Poland	 UK Plug-Pin Operation • Press down and slide out the "UK" button to slide out the "UK" plug-pin. Ensure the plug-pin is fully-extended and locked in position. To Retract • Firstly, press down and hold the "Retract" button; • Then press down and slide in the "UK" button to retract the "UK" plug-pin back to its original position. Compatible Countries Africa, Ireland, UK, Malaysia, Singapore, Hong Kong, Brunei, Dubai, The Commonwealth Countries	Technical Assistance If further technical assistance is required, please contact our customer care service team through our service & support hotline. SERVICE & SUPPORT HOTLINE Hotline: +65-6296 3038 WhatsApp: +65-6296 3038 Email: info@heanlee.com.sg  Customer Care Service SERVICE HOURS 9am - 4.30pm (Monday to Friday) Closed on Weekend and Public Holiday SERVICE LOCATION No.1 Genting Link, #03-04, Perfect One, Singapore 349518 Disclaimer This manual has been carefully checked, but it still does not exclude the possibility of spelling and technical errors. If the errors lead to inconsistencies with the actual situation, the actual situation shall prevail. Such errors or omissions cannot be used as a basis and will be revised in the new edition. All the contents of this manual, the company has the right to modify at any time, without notice.   3 Years Limited Warranty – Terms & Conditions Apply	Warranty Registration Please register your e-Warranty at https://soundtech.sg Warranty Serial: 63512 Model: TA-845C Product Description: Romi Adaptor With GaN PD 45W USB Quick Charger  Scan Me! to register e-Warranty @soundtech.sg Terms & Conditions 1. Limited warranty from Hean Lee Radio Service Pte Ltd (SOUNDTECH) applies to SOUNDTECH product with a valid warranty registration. 2. Warranty must be submitted online within seven(7) days of purchase to be valid. Submit online: https://soundtech.sg. Your SOUNDTECH product under this serial number is warranted against manufacturing defects, including parts, with a validity period of Thirty-Six (36) months from the date of purchase. 3. After warranty is registered online, a copy of proof of purchase of the product must be presented when requesting for warranty service/repair. This warranty shall not be transferable, negotiable or assignable to any third party. 4. This warranty only covers normal usage of the product and defects in material due to workmanship. 5. This warranty does not cover loss and immediately becomes void if damage to the product including appearance is due to accident, abuse, alteration, tampering, negligence, improper installation, wrong electrical supply, unauthorized repair, modification, acts of god, fire, civil unrest, usage not accordance with operation instruction manual and any other forms or misuse.	6. Any transportation, handling, delivery or other incidental charges incurred in respect of the product sent in for servicing shall be borne by the purchaser. The purchaser acknowledges and agrees that SOUNDTECH shall bear no responsibility for any product not bearing the SOUNDTECH brand and any other peripherals used in connection with the appliance. 7. SOUNDTECH reserves the right to compensate the buyer by way of exchange or additional repairs, whichever SOUNDTECH deems fit. No refunds will be issued. 8. Warranty is applicable only to SOUNDTECH products with valid warranty registered online. 9. SOUNDTECH service centre will contact customers for collection within seven(7) days from the date stated on the service receipt, otherwise informed. Serviced appliance not collected within twenty-one(21) days from the date stated on the service receipt will be disposed without prior notice.
--	---	--	--	---